

MODELS: GP 12-015 , GP 24-015, GP 12-030, GP 24-030

DC / AC INVERTERS

INVERTERS
SOFT START
12 - 24V
150 - 300 W

DESCRIPTION

Nordic Power Inverters are a good solution when you need AC-power in vehicles, caravans, boats and cabins. The inverter range covers from 150W up to 1000W. Both 12VDC and 24VDC input voltage available. The GP-models are equipped with Soft Start function for start-up protection.

FEATURES

- Soft Start
- Compact design
- Cig. lighter connector
- Modified sine-wave
- CE approved



300 W
GP12 - 030
GP24 - 030



150 W
GP12 - 015
GP24 - 015

WE RECOMMEND TO MEASURE
THE VOLTAGE BY RMS METER.

SPECIFICATIONS

MODEL	150 W		300 W	
	12 V	24 V	12 V	24 V
DC input voltag	10 - 15 V	20 - 30 V	10 - 15 V	20 - 30 V
Output power continious	150W	150W	300W	300W
Output power surg	450W	450W	1000W	1000W
Low battery alarm	10,5V ± 0,5V	21V ± 1V	10,5V ± 0,5V	21V ± 1V
Low battery shut-down	10V ± 0,5V	20V ± 1V	10V ± 0,5V	20V ± 1V
High battery shut-down	15,5V ± 0,5V	30V ± 0,5V	15,5V ± 0,5V	30V ± 0,5V
Short circuit protection	YES	YES	YES	YES
No load current	< 0,3 A	< 0,3 A	< 0,3 A	< 0,3 A
Alarm & thermal shut-down	60°C ± 0,5°C	60°C ± 0,5°C	60°C ± 0,5°C	60°C ± 0,5°C
Cigarette plug fuse	20A	10A	15A	10A
Alligator clip fuse	NO	NO	35A	20A
Dimensions (L x W x H)	165x91x58 mm	165x91x58 mm	190x91x58 mm	190x91x58 mm
Net weight	0,85 KGS	0,85 KGS	1,1 KGS	1,1 KGS

Batterieladegeräte

LADix System

DC/DC Wandler

Netzgeräte
AC/AC

Netzgeräte
AC/DC

Steckernetzgeräte
AC/AC

Steckernetzgeräte
AC/DC

Wechselrichter
DC/AC

Notstromversorgung
DC-UPS