



Specifications

Item number	605-12E	605-24E	1005-12E	1005-24E	1505-12E	1505-24E
Rated input voltage	12 V DC	24 V DC	12 V DC	24 V DC	12 V DC	24 V DC
Output Power:	600W		1000W		1500W	
Continuous	650W		1200W		1800W	
15 Minutes	1000W		2000W		3000W	
Surge	1000W		2000W		3000W	
Maximum input current	70A	40A	100A	50A	200A	100A
Output voltage 115VAC	115VAC +/- 3%					
230VAC	230VAC +/- 3%					
Output frequency	50 Hz or 60Hz to be specified					
Output wave form	Pure Sine Wave					
Total Harmonic Distortion	<3%					
Idle current 115VAC	<0.6A	<0.45A	<0.8A	<0.6A	<1A	<0.6A
Consumption 230VAC	<1A	<0.6A	<1.2A	<0.8A	<1.6A	<1A
Input voltage range	10.7V-15V	21.4V-30V	10.7V-15V	21.4V-30V	10.7V-15V	21.4V-30V
Low voltage alarm	10.7V	21.4V	10.7V	21.4V	10.7V	21.4V
Low voltage shutdown	10V	20V	10V	20V	10V	20V
Efficiency up to	85%					
Dimensions (L x W x H)	335 x 236 x 83 mm		395 x 236 x 83 mm		415 x 283 x 100 mm	
Weight	3 kgs		4 kgs		5.75 kgs	
Option Remote Control	Yes					
Option GFI	Yes					

Applications:

- Home electronics, office equipment, small tools and appliances.
- Battery chargers for camcorders, laptop computers, cellular phones & power tools.
- Ideal for camping, boating, caravans, mobile office, field work, emergency power and many other uses.
- Over 600W effect in high motor starting surge and can be used for hand tools, small refrigerator and most oxygen concentrators.

Batterieladegeräte

LADix System

DC/DC Wandler

Netzgeräte
AC/AC

Netzgeräte
AC/DC

Steckernetzgeräte
AC/AC

Steckernetzgeräte
AC/DC

Wechselrichter
DC/AC

**Sinus
Wechselrichter**

Notstromversorgung
DC-UPS