

MODELS: GP 12-060 , GP 24-060, GP 12-100, GP 24-100

DC / AC INVERTERS

INVERTERS
SOFT START
12 - 24V
600 - 1000 W

DESCRIPTION

Nordic Power Inverters are a good solution when you need AC-power in vehicles, caravans, boats and cabins. The inverter range covers from 150W up to 1000W. Both 12VDC and 24VDC input voltage available. The GP-models are equipped with Soft Start function for start-up protection.

FEATURES

- Soft Start
- Compact design
- Modified sine-wave
- CE approved



1000W
GP12 - 100
GP24 - 100

600 W
GP12 - 060
GP24 - 060

WE RECOMMEND TO MEASURE
THE VOLTAGE BY RMS METER.

SPECIFICATIONS

MODEL	600 W		1000 W	
	12 V	24 V	12 V	24 V
DC input voltage	10 - 15 V	20 - 30 V	10 - 15 V	20 - 30 V
Output power continious	600W	600W	1000W	1000W
Output power surge	1500W	1500W	2500W	2500W
Low battery alarm	10,5V ± 0,5V	21V ± 1V	10,5V ± 0,5V	21V ± 1V
Low battery shut-down	10V ± 0,5V	20V ± 1V	10V ± 0,5V	20V ± 1V
High battery shut-down	15,5V ± 0,5V	30V ± 0,5V	15,5V ± 0,5V	30V ± 0,5V
Short circuit protection	YES	YES	YES	YES
No load current	< 0,3 A	< 0,3 A	< 0,8 A	< 0,8 A
Alarm & thermal shut-down	60°C ± 0,5°C	60°C ± 0,5°C	60°C ± 0,5°C	60°C ± 0,5°C
DC input fuse	40A x 2	40A	35A x 4	30A x 2
Dimensions (L x W x H)	242x91x58 mm	242x91x58 mm	310x205x75 mm	310x205x75 mm
Net weight	1,7 KGS	1,7 KGS	5 KGS	5 KGS

Batterieladegeräte

LADix System

DC/DC Wandler

Netzgeräte
AC/AC

Netzgeräte
AC/DC

Steckernetzgeräte
AC/AC

Steckernetzgeräte
AC/DC

Wechselrichter
DC/AC

Notstromversorgung
DC-UPS